

# PDS-E 6GHz Power Splitter Series with N-Female Connector

Broadband Power Splitter for Wireless & Indoor Application, Support 555-6000MHz with 2-way, 3-way and 4-way



### **Technical features**

#### PRODUCT DESCRIPTION

RFS PDSE series Power Splitters have been designed for a variety of wireless applications in the frequency band from 555 to 6000MHz. The units evenly split and distribute wireless signals with minimal reflections or loss. The broad frequency range and outstanding PIM rating is ideally suited for multi-band distributed antenna systems or in combination with RADIAFLEX® radiating cables.

#### **FEATURES / BENEFITS**

### Broadband 555MHz-6000MHz

N-female interfaces PIM optimized design (160dBc @ 2x43dBm) Ideal for all kind of DAS applications Low insertion loss High power handling Small size, low weight



## **TECHNICAL FEATURES**

| <b>Electrical Specifications</b> |
|----------------------------------|
|----------------------------------|

| alcott leat o position to |     |          |  |  |  |  |
|---------------------------|-----|----------|--|--|--|--|
| Frequency Range           | MHz | 555-6000 |  |  |  |  |
| Power Rating              | W   | 300      |  |  |  |  |
| PIM 3rd @2*43 dBm         | dBc | 160      |  |  |  |  |
| Input Impedance           | Ohm | 50       |  |  |  |  |

### **Mechanical Specifications**

| Connectors        |    | N Female   |  |
|-------------------|----|--|--|
| Temperature Range | °C | -25 to +65 (+160 for 2hours in an event of fire,<br>encased in DragonSkin Cabinet) |  |
| IP Level          |    | IP66   |  |
| RoHS              |    | Compliant  |  |

**Model Number Specifications** 

| Model Number Specifications |         |  |  |  |  |  |
|-----------------------------|---------|--|--|--|--|--|
| Model Number                |         | PDS2E-555/6000                           | PDS3E-555/6000   | PDS4E-555/6000   |  |  |
| Number of Input Ports       |         | 1  |  |  |  |  |
| Number of Output Ports      |         | 2  | 3  | 4  |  |  |
| VSWR                        |         | 1.25@555-4900MHz<br>1.3:1@4900-6000MHz   | 1.25@555-4900MHz<br>1.3:1@4900-6000MHz                       | 1.25@555-3800MHz<br>1.3:1@3800-6000MHz   |  |  |
| Split Loss                  | dB      | 3  | 4.8  | 6.0  |  |  |
| Insertion Loss              | dB      | 0.2dB@555-2700MHz<br>0.35dB@2700-6000MHz | 0.2dB@555-2700MHz<br>0.45dB@2700-4900MHz<br>0.9@4900-6000MHz | 0.3dB@555-2700MHz<br>0.55dB@2700-3800MHz<br>0.75dB@3800-4900MHz<br>1.45@4900-6000MHz |  |  |
| Dimensions, L*W*H           | mm (in) | 270*66*25<br>(10.63*2.60*0.98)           | 205*65*46<br>(8.07*2.56*1.81)                                | 254*66*45<br>(10*2.60*1.77)  |  |  |
| Net Weight, ±10%            | kg (lb) | 0.43 (0.95)                              | 0.36 (0.79)  | 0.455 (1)  |  |  |

**External Document Links** 

Notes

LINK to VEX FILES

PDS-E 6GHz Power Splitter Series with N-Female Connector

REV : P1 REV DATE : 15 Nov 2025

www.rfsworld.com